


## Graduate Recessed (Pull-Up and Lay-In) Installation

220-240V / 50-60Hz  
IP20

**Terminal Labelling:**


<b>Power</b>	
L1	Switched Live
E	Earth
N	Neutral
<b>Emergency</b>	
L2	Unswitched Live
DA/AT3	DALI Autotest
DA/AT3	DALI Autotest
<b>Dimming</b>	
-/D1/DA	Analogue/DSI/DALI
+/D2/DA	Analogue/DSI/DALI
L3	Switch Dim / Corridor Function




**WARNING:** Luminaire must be earthed. Risk of electric shock from LED boards if operated with cover removed. Installation / operation outside of luminaires intended scope invalidates warranty. Suitable only for domestic / light industrial / industrial applications within the scope of EN55015. Tested to compliance with BSEN 60598: specification for general requirements and tests. Must be installed by a suitably qualified person in accordance with all relevant legislation. Ambient operating temperature of 0°C to 25°C. If maximum operating temperature is exceeded luminaire will automatically dim / switch off. Terminal blocks are rated to 16A unless stated otherwise. The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person. **LUMINAIRES WITH EMERGENCY PACK:** When supply is isolated battery output terminals may be live if battery is connected. Isolate mains and battery before servicing. Emergency luminaires require unswitched live connection taken from same phase as switched supply. When unswitched supply is connected status indicator illuminates green, when unswitched supply is disconnected indicator extinguishes and luminaire operates in emergency mode. 24 hour charge period required before undertaking full discharge test. Emergency test sheets provided should be used to record all emergency tests. Batteries should be replaced when 3 hour duration is not met. Excessive switching of permanent live may result in premature battery failure. Battery electrolyte can be harmful to eyes / open wounds, do not puncture, if electrolyte touches skin / eyes flush with water. Do not incinerate batteries.

### 1. Installation for Pull-up version


Remove both reflectors.




### 2. Pre-install x2 of the lumafix brackets to one side of the fitting.




### 3. Offer fitting up into ceiling, hooking one side of the fitting with the pre-fitted lumafix brackets onto the grid.



### 4. Install remaining lumafix brackets. Adjust positions as needed.




### 5. Wire the mains cable to the terminal block. Replace the reflectors. Installation complete.



### 6. Installation for Lay-in version

Install fitting up into ceiling grid, then wire mains into terminal block. Installation complete



# Graduate Recessed (Pull-Up and Lay-In) Installation

## Maintenance

- 1 Disconnect luminaire before undertaking any maintenance or cleaning.
- 2 Cleaning should be undertaken on external parts only using a slightly damp lint free cloth.
- 3 To remove reflectors, push on tabs to release.
- 4 Use a pan pozi screwdriver to remove LED tray and diffuser.
- 5 To remove components use a pan pozi screwdriver.

- 6 Please contact Dextra for assistance with spare component supply.

